



by Honeywell

600 Series IdentiFlex 602 with Velociti®

Description

The IdentiFlex 602 (IF602SS) with Velociti® is ideally suited for small- to medium-sized installations at commercial, institutional, and industrial life-safety projects.

The IF602SS has all the features of today's most advanced life safety systems. The integration of analog and addressable hardwired circuits allows system engineers to customize panels and maximize efficiency for any application.

The IF602SS can monitor and control up to 396 intelligent analog addressable input/output points. The interactive operator's display uses LED prompting for ease of programming and user operation. The alphanumeric display and keypad simplify the field programming, or the download programming from a Windows®-based application.

The IF602's housing was designed to be both aesthetically pleasing and functionally sound. The cabinet is designed to fit between studs for semi-flush mounting. This compact design and the key-activated dead-front construction enables secure routine maintenance of the system. Access to system function keys is limited by a key switch. Multiple levels of password protection prohibit unauthorized use. The circuit boards are mounted on a removable chassis, and are designed with pluggable terminal strips for ease of installation and service.

Operator's Display

The IF602SS's operator's display controls all user access to the system. The display provides all of the necessary keys and annunciation points to maintain and monitor the system. Alarm, supervisory, and trouble conditions are all indicated on the operator's display by dedicated LEDs and an internal sounder. The Acknowledge, Reset, and Signal Silence keys are located directly below the 4 x 40-character backlit alphanumeric display. All system functions and operational logic can be programmed from the front panel in the field. The IF602SS display has four user-programmable function keys.

SmartLink™ and SmartStart™ are trademarks and Velociti® Series is a registered trademark of Honeywell International Inc.

UL® is a registered trademark of Underwriters Laboratories, Inc.

Microsoft® Windows® is a registered trademark of Microsoft® Corporation.

Analog Addressable Control Panel



IF602SS

Features

- Listed per ANSI/UL® 864, 9th Edition
- One or two Signaling Line Circuits (SLC), up to 396 points
- Velociti protocol 99 detectors, 99 devices per Loop
- SmartStart™ self-programming logic
- Downloadable or front-panel programmable
- Password protected
- Approved for Supervisory Service
- Fully digital SLC protocol
- SmartLink™ peer-to-peer networkable
- 1000-event history log
- Automatic drift compensation
- Coded signaling capability
- Adjustable sensor sensitivity and temperature settings
- Style 6, 7 (Class A) or Style 4 (Class B) SLC
- Four Style Y (Class B), or two Style Z (Class A) notification appliance circuits (NACs)
- Semi-flush mounting (between 16" studs)
- 160-character display
- Optional GW-UDACT Compatible
- Built-in strobe and horn synchronization

An ISO 9000-2000 Company

SIGNALING



LISTED

S521



APPROVED



7165-1703:145

GAMEWELL-FCI

12 Clintonville Road, Northford, CT 06472-1610 USA • Tel: (203) 484-7161 • Fax: (203) 484-7118

Specifications are for information only, are not intended for installation purposes, and are subject to change without notice. No responsibility is assumed by Gamewell-FCI for their use.

©2009 Honeywell International Inc. All rights reserved.

www.gamewell-fci.com

CS-2490 Rev. B page 1 of 3

Analog Addressable Signaling Line Circuits

The IF602SS analog interface module provides Signaling Line Circuits (SLC), loop circuits that can monitor and control up to 198 analog/addressable devices on each power-limited loop, for a total of 396 analog points in a dual-loop system. Loop wiring is polarity sensitive.

Each SLC loop has a dedicated microprocessor that simultaneously communicates with connected field devices and the main CPU.

The IF602SS uses Velociti[®] fully digital communications protocol to improve the speed and accuracy of event reporting. The communications protocol provides for alarm verification per detector, detector adjustability and compensation, adjustable analog heat detector range circuit isolation, and priority interrupts. Priority interrupts allow contact-type devices such as manual fire alarm stations to interrupt the polling cycle and transmit their addresses at any time during a polling sequence.

The fully digital protocol allows the IF602SS to operate on most types of field wiring, greatly expanding its use in retrofit applications. Consult the Supplemental SLC Manual or Gamewell-FCI Technical Support for specific wiring requirements.

IF602SS Power Supply

The IF602SS power supply is a fully regulated 8 amp. supply that furnishes system operating and signaling power. It is equipped with a battery charger which maintains the secondary power source. The power supply is monitored by the main CPU, ensuring that adequate power levels are available. The power supply design allows for high efficiency while providing precise power output. The battery charger maintains batteries up to 26 AH. The supply powers four on-board Notification Appliance Circuits (NACs) (two Class A) with the multiple built-in synchronization protocols for System Sensor, Cooper-Wheelock and others.

Input (I) / Output (O) Devices

Addressable control output devices are the interface between analog circuits and building functions. The outputs are controlled with Control By Event (CBE) software within the IF602SS, and can be programmed to respond to any event. The control devices can be used as supervised remote signaling circuits.

The IF602SS, with Gamewell-FCI's complete line of 600 Series devices, provides a foundation for system design. The IF602SS's RS-232 output expands system monitoring and control capabilities.

Remote Display and Control

Serial annunciator drivers are available in 16-point increments and are an ideal interface to graphic annunciators. The serial annunciators display system activity and control. Switches can be used for Acknowledge, Reset, Signal Silence, Drill, etc., to customize the remote status control network.

An alphanumeric display can also be used for remote status and control. The alphanumeric display is designed to communicate over the serial communications network.

The IF602SS can communicate locally or remotely with a printer to document system activity.

See the RAN/SAN data sheet (CS-2025 and CS-2027) for complete annunciator details.

Applications

The IF602SS Analog Addressable Control Panel is designed for new or retrofit small- to mid-sized projects that require state-of-the-art life-safety systems. The embedded CPU offers users unrivaled reliability without sacrificing flexibility or value.

With compatible analog sensors and addressable input and control interface devices, and its remote status and control capabilities, the IF602SS provides system engineers with all the tools necessary to design effective system solutions for any application.

Architectural/Engineering Specifications

The control panel furnished and installed shall be capable of supporting 396 addressable devices and two analog loops. The panel shall use a fully digital Signaling Line Circuit (SLC) protocol. The panel shall contain four on-board Notification Appliance Circuits (NACs) that support the multiple synchronization protocols. The panel shall use a 160-character Liquid Crystal Display (LCD) and a 1,000-event history log. The panel shall be a Gamewell-FCI IF602SS with Velociti.

GAMEWELL-FCI

12 Clintonville Road, Northford, CT 06472-1610 USA • Tel: (203) 484-7161 • Fax: (203) 484-7118

Specifications

Common Control:

Standby Current: 0.160A
Alarm Current: 0.226A plus signaling circuit power, plus 0.002A for master box, or plus 0.022A for reverse-polarity
Input Power: 120 VAC, 4.0A; or 240 VAC, 2.0A

Auxiliary Output:

S+/S-, A+/A-: 2.0 A maximum
Common Relays: 1.0A @ 30 VDC, or 0.5A @ 250 VAC

Notification Appliance Circuits:

Circuits: Four Class B, two Class A
Output: 3.0A maximum@24 VDC per circuit. Maximum 7.5A total for all circuits

Analog SLC:	198	396
Standby Current:	0.035A	0.055A
Alarm Current:	0.045A	0.055A

Panel Dimensions:

Standard Cabinet: 20.0" H x 14.0" W x 4.5" D
 (50.8 H x 35.6 W x 11.4 D cm)

Battery Storage Dimensions:

Standard Cabinet: 6.0" H x 9.0" W x 4.5" D
 (15.24 H x 22.86 x 11.43 D cm)
Relative Humidity: 93% non-condensing
Temperature Rating: 32°F – 120°F (0°C – 49°C)

Ordering Information

Model	Description
GWIF602SS-198R	IF602SS Analog Addressable System with Velociti consisting of the following: <ul style="list-style-type: none"> • IF602SS common control • 8 amp. main power supply • One (1) analog circuit module (198 analog addressable points) • Standard cabinet assembly (CAB-602R) Standard Cabinet: 20.0" H x 14.0" W x 4.5" D (50.8 H x 35.6 W x 11.4 D cm)
GWIF602SS-396R	IF602SS analog addressable system with Velociti, consisting of the following: <ul style="list-style-type: none"> • IF602SS common control • 8 amp main power supply • Two (2) analog circuits module (396 analog addressable points) • Standard cabinet assembly (CAB-602R) Standard Cabinet: 20.0" H x 14.0" W x 4.5" D (50.8 H x 35.56 W x 11.43 D cm)
52358	IdentiFlex 602SS Analog/Addressable Fire Alarm Control Panel Installation and Operation Manual
GW31077	CTM-602, city-tie/remote signaling module for 602 Series panels.
GW31078	ISO-232, RS-232 serial-port isolator module for 602 Series panels.
GW31079	CLA-602, Class "A" adapter module for SLC, 602 Series panels.
GW70703	Coiled Programming Cable