

CMP-2401B/CMP-2402B

One- and Two-Zone, Class B Conventional FACPs



Conventional Fire Alarm Control Panels

General

Fire-Lite's Canadian Mini-Panel Series consists of the CMP-2401B and CMP-2402B, one- and two-zone, Class B, conventional Fire Alarm Control Panels (FACPs). These panels meet current ULC requirements. The MiniPanels meet a variety of low-end commercial, industrial, and institutional applications.

Features

- One- or two-zone non-expandable construction.
- One (CMP-2401B) or two (CMP-2402B) Class B Initiating Device Circuit(s) (IDCs).
- IDC(s) support normally-open contact devices and two-wire smoke detectors. *Refer to Fire•Lite Device Compatibility Document for listed compatible devices.*
- Single built-in, Class B Notification Appliance (Signal) Circuit (NAC).
- 1.25 amps of NAC power.
- NACs feature 60-second Silence Inhibit, standard.
- Alarm and Trouble relays standard (Form-C).
- 24-volt operation.
- Resettable four-wire smoke detector power @ 85 mA.
- Integral battery charger capable of charging up to 7 AH batteries.
- Battery deep discharge protection.
- Reverse polarity protection.
- Fuseless, power-limited technology meets all the latest ULC power-limiting requirements.
- Control switches for:
 - Reset.
 - Trouble Silence.
 - Signal Silence: Zone One.
 - Signal Silence: Zone Two (CMP-2402B only).
- LED indicating lamps:
 - AC Power (Alimentation): GREEN.
 - Zone Alarm (Alarme Zone #): RED.
 - Zone Trouble (Trouble Zone #): YELLOW.
 - Bell Trouble (Trouble Cloche): YELLOW.
 - Option Module Trouble (Trouble Option): YELLOW.
 - System Trouble (Trouble Systeme): YELLOW.
 - Zone Silence (M.S. Silence Zone): YELLOW.
 - Ground Fault (Faute M.A.L.T.): YELLOW.
 - Battery Trouble (Trouble Piles): YELLOW.
- Integral piezo sounder signaling provides:
 - Alarm – steady signal.
 - Trouble – pulsed signal.
- Electronics and operational controls fully enclosed in lockable cabinet capable of housing 7 AH batteries.
- Standard dead-front dress panel, as required by ULC.
- RTB Remote Trouble Buzzer option.
- Local energy or remote station connection with optional 4XTMF.



cmp2401.jpg

Specifications

- **AC Power:**
 - 120 VAC, 60 Hz, 0.5 amps.
 - Fuse F2 – 2 amp, 3AG Slow Blow.
- **Wire size:** Minimum #14AWG (2.0 mm²) wire with 600 V insulation.
- **Notification appliance (signal) power:** 1.25 amps.
- **Maximum battery charging capacity:** 7 AH.

INITIATING DEVICE CIRCUITS (ZONES)

- One Class B: CMP-2401B.
- Two Class B: CMP-2402B.
- Zones support:
 - Two-wire smoke detectors and any normally-open contact devices.
- All circuits are power-limited and supervised, meeting the latest ULC requirements using fuseless technology.

NOTIFICATION APPLIANCE CIRCUIT (NAC)

- One Class B @ 1.25 amps
- NACs include 60-second Silence Inhibit feature, standard.
- All circuits are power-limited and supervised, meeting the latest ULC requirements using fuseless technology.

AUXILIARY OUTPUTS

- Resettable four-wire smoke detector power @ 85 mA.
- Integral Form-C Alarm and Trouble relays, rated at: 2.0 amps @ 30 VDC (resistive), 2.0 amps @ 30 VAC (resistive).

CABINET SPECIFICATIONS

The cabinet is red. Knockouts on the top, sides, and back provide ease of wire entry. The compact cabinet can be surface- or semi-flush mounted.

Cabinet measurements: 36.83 cm high x 31.75 cm wide x 7.303 cm deep. **Outer measurements of optional trim ring:** 44.766 cm high x 42.288 cm wide.

Product Line Information

CMP-2401B: 24-Volt, 1-zone, Class B, ULC listed FACP. Includes dead-front dress panel.

CMP-2402B: 24-Volt, 2-zone, Class B, ULC listed FACP. Includes dead-front dress panel.

TR-3-R: Semi-flush trim ring, red.

RTB: Optional Remote Trouble Buzzer.

4XTMF: Optional Remote station output or municipal box connection.

BAT-1270: Battery, 12 volt, 7.0 AH (two required).

2401BRB: Replacement board for CMP-2401B.

2402BRB: Replacement board for CMP-2402B.

29050: Replacement power supply.

Listings and Approvals

These listings and approvals apply to the basic CMP-2401B/CMP-2402B. In some cases, certain modules may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- ULC: UOJZC.S624

Fire•Lite Alarms® is a registered trademark of Honeywell International Inc.
©2009 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice.

For more information, contact Fire•Lite Alarms.
(888) 289-1114
10 Whitmore Road
Woodbridge, Ontario L7L 7Z4
www.firelite.com

